

ILM-100

Insertion Loss Meter



Product Overview

The Insertion Loss Meter, ILM-100, was designed to measure insertion loss on fiber optic components quickly and accurately. The system has a built-in stabilized laser source for single-mode applications or LED source for multi-mode applications. With a dual wavelength configuration, insertion loss can be measured for two wavelengths in less than 1 second. ILM-100 system comes with both USB and ethernet control for ease of integration into test systems.

Features

- Compact benchtop instrument for all-in-one operation
- USB and Ethernet interface
- Test software OPL-CLX available for logging measurements
- Fully automated single and dual wavelength insertion loss measurements
- Multi-mode instruments available with define launch conditions (EF, AS100, 70/70, etc.)
- Various detector options
- Customizable sources and fiber types
- Interchangeable adapter interface




Applications

- Cable assembly testing
- Optical alignment
- Signal monitoring



Compliance

- IEC-61300-3-4





USB and Ethernet Communication

With both USB and Ethernet communication interfaces, the ILM-100 can be easily integrated into any production automation environment. The ILM-100 is compatible with the OPL-CLX software, perfect for performing cable assembly measurements, recording results in database and printing results.

Multi-mode Launch Condition Control

ILM-100 multi-mode sources can be internally configured to meet launch condition requirements for specific applications. No need to have an external modal conditioner.



Customizable Source and Detector Types

ILM-100 can accommodate many different fiber optic source types depending on your requirements: DFB, FP, LED, etc. Along with many different fiber types and optical power meter types, ILM-100 is one of the most configurable insertion loss meters on the market.

ILM Optical / Electrical Specifications

Parameter	Specification	
	Single-mode	Multi-mode
Fiber Type (μm)	9/125	50/125, 62.5/125 or 100/140
Launch Condition	N/A	Available upon request
Nominal Wavelengths (nm) ¹	1310 / 1490 / 1550 / 1625	850 / 1300
Output Power (typical) (dBm)	0	-18 / -21
Source Stability (dB) ²	± 0.02	
Detector Type	1 mm InGaAs / 3 mm InGaAs	
Power Range (dBm)	6 to -72 / 3 to -72	
Detector Linearity (dB) ³	± 0.02 (< 10 dB)	
	± 0.05 (> 10 dB)	
Detector Total Uncertainty (dB) ⁴	± 0.25	
Remote Interface	USB or Ethernet	
Display	4.3" touch screen	
	Input: 90 - 264 V AC, 47 - 63 Hz	
Power Supply	Output: 18V DC, 5 A	
	36 maximum	
Power Consumption (VA)	36 maximum	

Notes:

¹ Custom sources available upon request

² Over 1 hour with maximum temperature variation of 1 °C

³ Measured at 1490 nm, between 3 to -65 for 1 mm, 0 to -65 for 3 mm

⁴ At calibration conditions for all NIST traceable wavelengths

Mechanical / Environmental Specifications

Parameter	Specification
Max Channel Count	24
Unit Dimension W x H x D (cm)	42.5 x 8.9 x 20.3
Operating Temperature (°C)	5 to 40
Humidity (Non-condensing)	Maximum 80% RH ¹

Notes:
¹ From 5 to 31 °C, decreasing linearly to 50% RH at 40 °C

In the Box

ILM-100- Insertion Loss Meter

- ILM-100
- 18V AC-DC Power Supply
- Power Cable
- USB Cable

Ordering Scheme & Instructions

1. Configure ILM Insertion Loss Meter

Single-mode version

ILM-100- [] [] - [] - [] -09- [] []



CHANNELS		SOURCES		DETECTOR		CONNECTOR	
01	1	3	1310 nm	IN1	1 mm InGaAs	FA	FC/APC
08	8	4	1490 nm	IN3	3 mm InGaAs	FP	FC/UPC
12	12	5	1550 nm	R	Remote-head	SA	SC/APC
16	16	6	1625 nm			SP	SC/UPC
24	24	35	1310 / 1550 nm			EA	E/2000
		46	1490 / 1625 nm				
		3456	1310 / 1490 / 1550 / 1625 nm				

Multi-mode version

ILM-100- [] [] - [] - [] - [] - [] []



CHANNELS		DETECTOR		CONNECTOR		SOURCES		FIBER	
01	1	IN1	1 mm InGaAs	FA	FC/APC	8	850 nm	50	50/125 μm
08	8	IN3	3 mm InGaAs	FP	FC/UPC	3	1310 nm	62	62.5/125 μm
12	12	R	Remote-head	SA	SC/APC	83	850 / 1310 nm	100	100/140 μm
16	16			SP	SC/UPC				
24	24			EA	E/2000				



Santec Regional Sales Offices

SANTEC CORPORATION

5823 Ohkusa-Nenjozaka, Komaki,
Aichi, 485-0802, Japan
Tel: +81-568-79-3536 | Fax: +81-568-79-1718

Santec Europe Ltd.

99 Park Drive, Milton Park, Abingdon,
Oxfordshire, OX14 4RY, United Kingdom
Tel: +44-20-3176-1550

SANTEC U.S.A. CORPORATION

433 Hackensack Ave., Hackensack
NJ, 07601, USA. Toll Free: +1-800-SANTEC1 (726-8321)
Tel: +1-201-488-5505 | Fax: +1-201-488-7702

Santec (Shanghai) Corporation Limited

21F Room H, Hua Du Bldg., No.838 Zhangyang Road
Pudong District, Shanghai, 200122, China
Tel: +86-21-5836-1261 | Fax: +86-21-5836-1263

2022© SANTEC CORPORATION Santec reserves the right to make changes in equipment design, components or specifications without notice.

ILM-100-C-E/Ver.1.0 CODE-202303-MB-KT-CPY